


PYROELECTRIC IR SENSOR THERMOPILE SENSOR



We Make Good World with Sensor



©Tottori Pref.

Application Guide

Pyroelectric IR sensor

The pyroelectric infrared sensor is an infrared sensor that applies the pyroelectric effect of ferroelectric ceramic. It can detect human body movement and so on with sensing temperature changes.



Lighting

Automatic switch control.
Energy saving, Comfort & Convenience.



Security

Security & Safety.



Air-conditioner

Comfort & Energy saving.



**IP camera
IoT**

Camera control. Energy saving & battery life extension. Security, Surveillance & Pet monitor.



Toilet

Automatic toilet lid open and close. Comfort, Convenience & Cleanliness.



TV

Automatic display control.
Energy saving & comfort.

Thermopile sensor

Thermopile sensor unit

Thermopile sensor is an infrared sensor that applies the Seebeck effect. With detecting absolute thermal amount of the object, it measures temperature without contact.



Printer

Temperature monitor of inside parts. Printing quality and efficiency improvement.



Automotive

Temperature measurement of seat space, passenger, heat generation parts and etc.. Comfort and safety improvement.



Microwave oven

Food temperature measurement. Heat control to preset temperature.



Air-conditioner

Temperature monitor of floor and human body. Comfortability control & energy saving control.



IH cooker

Temperature monitor of pot bottom. Automatic control of cooking temperature.



Ear thermometer

Quick measure of body temperature.

Air-conditioner	Application					Object (Target temperature)	Part number	Number of element	FOV [°]		Shape	Output method	Feature	Data sheet
	Microwave oven	IH cooker	Printer	Ear thermometer	Non-contact thermometer				X-axis	Y-axis				
O						Floor temperature (-20~60°C)	A3D01S-FB-50-60	1	90	90	TO-5 detector	SMBus	* Wide-angle detection	5
O						Floor temperature (-20~60°C)	A1D08A-BU-50-60	8 (8x1)	44	5	TO-5 detector	SMBus		7
O						Floor temperature (-20~60°C)	A1D16B-AU-50-60	16 (4x4)	88	88	TO-5 detector	SMBus		8
	O					Food (-20~120°C)	A1D01S-AU-50-120	1	22	22	TO-5 detector	SMBus		
	O					Food (-20~120°C)	A1D08A-BU-50-120	8 (8x1)	44	5	TO-5 detector	SMBus		
	O					Food (-20~120°C)	A1D16B-AU-50-120	16 (4x4)	88	88	TO-5 detector	SMBus		
		O				Pot surface (-20~300°C)	A3D01S-AU-50-300	1	22	22	TO-5 detector	SMBus	* Temperature drift performance improvement	9
			O			Thermal roller	A3D01S-CU-50-300	1	12	12	TO-5 detector	SMBus	* Forcused detection	15
			O			Thermal roller	A3A01S-CU-33-300	1	12	12	TO-5 detector	analog	* Forcused detection	16
9				O		Human Body temperature	TS-S2NMB-2R	1	90	90	TO-18 detector	2-channel	* Tab-less model	17
				O		Human Body temperature	TS-S2NMB-2RT	1	90	90	TO-18 detector	2-channel		18
#					O	Multi purpose	TS-S2NAB-2R	1	90	90	TO-5 detector	2-channel		19
					O	Multi purpose	TS-S2NAU-2C	1	12	12	TO-5 detector	2-channel		20


Thermopile sensor

Nicera

A3D01S-FB-50-60


■ Applications Air-conditioner
(Floor temperature monitor)
Target temperature -20~60°C

■ Feature ASIC built-in thermopile (I2C output)
Wide-angle detection (Single element)




TO-5


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Operating Voltage		4.5	5	5.5	V
Detection Temperature		-20		400	°C
Operating Temperature		-20		100	°C
Storage Temperature		-30		105	°C
Accuracy		-2		+2	°C
Time Constant				200	msec.

Analog
Amp build-in
ASIC build-in

SMD

Air-conditioner
Microwave oven

IH cooker

Printer

Ear thermometer
Non-contact thermometer


Thermopile sensor

Nicera

A3A01S-FB-33-60


■ Applications Air-conditioner
(Floor temperature monitor)
Target temperature -20~60°C

■ Feature ASIC built-in thermopile (Analog output)
Wide-angle detection (Single element)




TO-5


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Operating Voltage		3	3.3	3.6	V
Detection Temperature		-20		60	°C
Operating Temperature		-20		100	°C
Storage Temperature		-30		105	°C
Accuracy		-2		+2	°C
Time Constant				200	msec.


Thermopile sensor

Nicera

A1D08A-BU-50-60


■ Applications Air-conditioner
(Floor temperature monitor)
Target temperature -20~60°C

■ Feature ASIC built-in thermopile (I2C output)
8 array element





TO-5

Dimensions




FOV



Analog	Amp build-in	ASIC build-in
SMD		

Air-conditioner	Microwave oven	IH cooker
Printer		
thermometer		

Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Operating Voltage		4.5	5	5.5	V
Detection Temperature		-20		60	°C
Operating Temperature		-20		100	°C
Storage Temperature		-30		105	°C
Accuracy		-2		+2	°C
Time Constant				200	msec.


Thermopile sensor

Nicera

A1D16B-AU-50-60


■ Applications Air-conditioner
(Floor temperature monitor)
Target temperature -20~60°C

■ Feature ASIC built-in thermopile (I2C output)
4 x 4 square element




TO-5


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Operating Voltage		4.5	5	5.5	V
Detection Temperature		-20		60	°C
Operating Temperature		-20		100	°C
Storage Temperature		-30		105	°C
Accuracy		-2		+2	°C
Time Constant				200	msec.


Thermopile sensor

Nicera

A3D01S-AU-50-120


■ Applications **Microwave oven
(Food temperature detection)**
Target temperature -20~120°C

■ Feature **ASIC built-in thermopile (I2C output)
Single element**




TO-5


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Operating Voltage		4.5	5	5.5	V
Detection Temperature		-20		400	°C
Operating Temperature		-20		100	°C
Storage Temperature		-30		105	°C
Accuracy		-2		+2	°C
Time Constant				200	msec.

Analog
Amp build-in
ASIC build-in

SMD

Air-conditioner
oven

Microwave
oven

IH cooker

Printer

Ear
thermometer
Non-contact
thermometer


Thermopile sensor

Nicera

A3A01S-AU-33-120


■ Applications **Microwave oven
(Food temperature detection)**
Target temperature -20~120°C

■ Feature **ASIC built-in thermopile (Analog output)
Single element**




TO-5


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Operating Voltage		3	3.3	3.6	V
Detection Temperature		-20		120	°C
Operating Temperature		-20		100	°C
Storage Temperature		-30		105	°C
Accuracy		-2		+2	°C
Time Constant				200	msec.


Thermopile sensor

Nicera

A1D08A-BU-50-120


■ Applications **Microwave oven**
(Food temperature detection)
 Target temperature -20~120°C

■ Feature **ASIC built-in thermopile (I2C output)**
8 array element




TO-5


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Operating Voltage		4.5	5	5.5	V
Detection Temperature		-20		120	°C
Operating Temperature		-20		100	°C
Storage Temperature		-30		105	°C
Accuracy		-2		+2	°C
Time Constant				200	msec.

Analog
Amp build-in
ASIC build-in

SMD

Air-conditioner
Microwave
oven

IH cooker

Printer

Ear
thermometer
Non-contact
thermometer


Thermopile sensor

Nicera

A1D16B-AU-50-120


■ Applications **Microwave oven
(Food temperature detection)**
Target temperature -20~120°C

■ Feature **ASIC built-in thermopile (I2C output)
4 x 4 square element**




TO-5


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Operating Voltage		4.5	5	5.5	V
Detection Temperature		-20		120	°C
Operating Temperature		-20		100	°C
Storage Temperature		-30		105	°C
Accuracy		-2		+2	°C
Time Constant				200	msec.

Thermopile sensor


Nicera

A3D01S-CU-50-300

■ Applications IH Cooker


(Pot surface temperature detection)
Target temperature -20~300°C

■ Feature ASIC built-in thermopile (I2C output) Focused detection (Single element)




TO-5


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Operating Voltage		4.5	5	5.5	V
Detection Temperature		-20		400	°C
Operating Temperature		-20		100	°C
Storage Temperature		-30		105	°C
Accuracy		-3		+3	°C
Time Constant				200	msec.

Analog
Amp build-in
ASIC build-in
SMD

Air-conditioner
Microwave
oven

IH cooker

Printer

Ear
thermometer
Non-contact
thermometer

Thermopile sensor

Nicera

A3A01S-CU-33-300


■ Applications IH Cooker

(Pot surface temperature detection)

Target temperature -20~300°C


■ Feature ASIC built-in thermopile (Analog output)

Focused detection (Single element)




TO-5


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter


Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Operating Voltage		3	3.3	3.6	V
Detection Temperature		-20		300	°C
Operating Temperature		-20		100	°C
Storage Temperature		-30		105	°C
Accuracy		-3		+3	°C
Time Constant				200	msec.

Thermopile sensor

A3D01S-CU-50-300


■ Applications Printer
(Thermal roller temperature detection)

■ Feature ASIC built-in thermopile (I2C output)
Focused detection (Single element)




TO-5


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Operating Voltage		4.5	5	5.5	V
Detection Temperature		-20		400	°C
Operating Temperature		-20		100	°C
Storage Temperature		-30		105	°C
Accuracy		-3		+3	°C
Time Constant				200	msec.

Analog
Amp build-in
ASIC build-in

SMD

Air-conditioner
Microwave
oven

IH cooker
Printer

thermometer
Ear

Non-contact
thermometer


Thermopile sensor

Nicera

A3A01S-CU-33-300


■ Applications Printer
(Thermal roller temperature detection)

■ Feature ASIC built-in thermopile (Analog output)
Focused detection (Single element)




TO-5


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Operating Voltage		3	3.3	3.6	V
Detection Temperature		-20		300	°C
Operating Temperature		-20		100	°C
Storage Temperature		-30		105	°C
Accuracy		-3		+3	°C
Time Constant				200	msec.

Thermopile sensor

TS-S2NMB-2R

Nicera


■ Applications Ear thermometer
(Human body temperature detection)

■ Feature Object-Sensor temperature detection
(2-channel)
Single element, Tab-less model




TO-18


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Sensitivity Output	323K at shutter opening	1.82	2.43	3.03	mV
Resistance of thermopile		145	175	205	kΩ
Thermistor resistor	25°C	95	100	105	kΩ
Operating Temperature		-30		100	°C
Time Constant		25	50	80	msec.

Analog
Amp build-in
ASIC build-in

SMD

Air-conditioner
Microwave
oven

IH cooker
Printer

Ear
thermometer

Non-contact
thermometer

Thermopile sensor

Nicera

TS-S2NMB-2RT


■ Applications Ear thermometer
(Human body temperature detection)

■ Feature Object-Sensor temperature detection
(2-channel)
Single element






TO-18


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Sensitivity Output	323K at shutter opening	1.82	2.43	3.03	mV
Resistance of thermopile		145	175	205	kΩ
Thermistor resistor	25°C	95	100	105	kΩ
Operating Temperature		-30		100	°C
Time Constant		25	50	80	msec.

Thermopile sensor

TS-S2NAB-2R


Nicera

■ Applications Non-contact thermometer


■ Feature Object-Sensor temperature detection
(2-channel)
Wide-angle detection (Single element)

Dimensions


TOP VIEW



SIDE VIEW




BOTTOM VIEW




Tolerance with no specified : +/- 0.2

FOV




Circuit diagram



■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Sensitivity Output	323K at shutter opening	1.5	2	2.5	mV
Resistance of thermopile		145	175	205	kΩ
Thermistor resistor	25°C	95	100	105	kΩ
Operating Temperature		-30		100	°C
Time Constant		25	50	80	msec.



TO-5

Analog
Amp build-in
ASIC build-in

SMD

Air-conditioner
Microwave oven

IH cooker

Printer

Ear thermometer

Non-contact thermometer


Thermopile sensor

TS-S2NAU-2C

Nicera


■ Applications Non-contact thermometer

■ Feature Object-Sensor temperature detection
(2-channel)
Focused detection (Single element)




TO-5


Dimensions



FOV



Circuit diagram



Tolerance with no specified : +/- 0.2

■ Main Parameter

Parameter	Condition	Spec.			Unit
		Min.	Typ.	Max.	
Sensitivity Output	323K at shutter opening	0.42	0.57	0.71	mV
Resistance of thermopile		145	175	205	kΩ
Thermistor resistor	25°C	95	100	105	kΩ
Operating Temperature		-30		100	°C
Time Constant		25	50	80	msec.

1. Design restrictions/precautions

These sensors are designed for indoor use. If used for outdoor applications, please be sure to apply proper supplementary optical filter, drip-proof and anti-dew construction.

In cases where secondary accidents caused by operation failure or malfunction of the sensor could be expected, please include a fail safe function into the design.

2. Remarks

These sensors are not suitable for applications that require extremely high reliability, such as related to human life (life supporting devices and etc.).

These sensors must not be used for products that are prohibited to manufacture, use and sell by Japanese domestic and foreign laws and orders.

The contents described in this catalog are as of January 2021.

The described contents may be changed or suspended without notice.

Agent:Real Chance Co.,Ltd Taiwan:+886-2-2908-8287 China:+86-0769-82388628
<http://www.realchance.com.tw>

Nippon Ceramic Co., Ltd.

Technical Center

176-17, Hirooka,
Tottori-shi 689-1193 JAPAN
TEL +81-857-53-3600
(Pilot)
FAX +81-857-53-3676
Mail ip-sales@nicera.co.jp

Nicera European Works Ltd.

- NEW -
25 Copinger Close, Totton,
Southampton, Hants,
SO40 8WN United Kingdom
TEL +44-2380-667908
FAX +44-2380-663758

Nicera Hong Kong Ltd.

- NHK -
Unit L1, 5/F, Phase 2,
Kaiser Estate,
NOS 47-53 Man Yue Street,
Hung Hom, Kowloon,
Hong Kong, China
TEL +852-2795-7511
FAX +852-2754-3957

Nicera America Corp.

- NAC -
16461 Sherman Way,
Suite 248, Van Nuys,
CA 91406, USA
TEL +1-818-779-2100
FAX +1-818-779-2111

<https://www.nicera.co.jp/>